

8IN1 DVB-C SD Encoder Modulator



Overview

SD Encoder Modulator supports 8xCVBS and 8 pairs of unbalanced audio and IP input and 1xRF output. After coded and modulated, the input signal can be directly output or mixed output with original TV signal. It can be widely used in home entertainment, security and protection monitoring, hotel LCD panels, shopping mall advertising and other similar places.

Feature

- ◆ Integrated encoder and modulator
- ◆ 8CVBS+Audio and IP input
- ◆ DVB-C RF out
- ◆ RF Range: 47-870Mhz
- ◆ Keyboard+LCD control and network management

Technical Specification

Input	Video Signal	8xCVBS, BNC interface, level 1.0 Vp-p
-------	--------------	---------------------------------------

	Audio Signal	8 pairs of unbalanced audio, BNC interface, level 2.0 Vp-p	
	IP	IP pass-through	
	Video Coding	comply with ISO11172 (MPEG-1) & ISO13818 (MPEG-2)	
		MPEG-2 coding adopt MP@ML (4:2:0)	
		MPEG-2 Adaptive Field Frame (AFF)	
		MPEG-2 Field-Based (FB)	
	Resolution	720×576 (PAL); 720×480 (NTSC)	
	Bit Rate	1.0~15Mbps continuously adjustable per channel	
Audio Coding	Sampling	32KHz, 44.1KHz, 48KHz	
	Code Rate	64, 96, 128, 256, 384Kbps	
	Property	MPEG-1, Layer 1/2	
	Output	1×DVB-C RF (47-870MHz), F-head	
DVB-C Modulation	Frequency Range: 47~870MHz, 1KHz step		Output Level: 80-110dB
	Constellation: 16/32/64/128/256-QAM		Symbol Rate: 5-9Msps
	Error-Correcting Codes: RS code 188/204		BER: 0
	Impedance: 75Ω		MER: ≥32dB
	Level Attenuation Range: 0~30dB (0.5dB step)		
General Features	Size	482mm×410mm×44mm	
	Temperature Range	0~45°C (operation); -20~80°C (storage)	
	Power	100-240VAC, 50Hz, 25W	